# NEC SV9300 Telephone Quick Reference

#### <u>Dial Out</u>

- Lift handset or press Speaker key
- Dial 9 (system will automatically grab an available line for you)

<u>Speaker Phone Note</u>: When using the **Speaker Phone** you must have your **MIC** we lit **RED** in order for the caller to **hear you**, turn the **MIC** key **off** if you would like to **Mute** the **Speaker Phone** 

# Parking a Call

- · With an active call, Press the Park Set key & look at the display
- The system will **automatically** assign the next available park number. Ex. Park 00
- Call employee and advise them to pick up the designated park number. Ex. Park 00

**To Pick Up a Parked Call**: **Lift handset**, press the **Park P/U** key & **enter** the **park number** to pick up. Ex. 00 **<u>NOTE</u>**: Placing a call **ON HOLD** will keep your call on your **PERSONAL CALL KEY** and **NO ONE** else will be able to retrieve it (must be placed on park for other employees to retrieve call)

#### <u> Placing a Call on Hold</u>

With an active call, Press the Hold weg

**NOTE**: When placing a call on hold, another employee will NOT be able to retrieve the call. Hold is exclusive for yourself. If you need an employee to take that call, you will need to transfer it to them.

To Pick Up the Held Call: Press the flashing Call 1 or Call 2 key -

#### <u>Transfer a Call</u>

- Dial Extension Number or 9 + Phone Number, announce call (optional)
- Hang up for call to be transferred


Note: Press 9 after the extension to transfer call directly to voicemail

#### Intercom Calls

- Lift handset (or press Speaker wey)
- · Dial Extension Number

# **Conference call**

- 1. Make or receive first call (internal or external)
- 2. With the active call, Press the Transfer key -
- 3. Make or receive second call (internal or external)
- 4. Press **Conf** key soft key to join all calls —



| Re | dial                             | MARY SMITH<br>11:00 AM SUN 1 J | [200]<br>UN 2014 |            |        |      |          |           |             |
|----|----------------------------------|--------------------------------|------------------|------------|--------|------|----------|-----------|-------------|
|    | Press the <b>HITS</b> soft key • |                                |                  |            |        |      | ing Call | s]        | 01          |
| •  | Press OG (Outgoing) soft h       | (ey 🔶 💁                        |                  | IC         |        | 1 30 | 11:00    | JAMES S   | MITH<br>201 |
| •  | Press ↑Prev ↓Next to s           | croll through th               | ne last 10 ou    | utgoing nu | mbers— |      | Redial   | 1<br>Prev | ↓Next       |
| •  | Press Redial Soft key to c       | omplete call 🕂                 | Redi             | al ↑Prev   | ↓Next  |      |          |           |             |
|    |                                  | . –                            |                  |            |        |      |          |           |             |

Or press Speaker key to Exit



| <u>Cal</u> | ller ID                         | MARY SMITH<br>11:00 AM SUN 1 | [200]<br>L JUN 2014 |         |          |        | [ [Incom | ning Call | sl           | <b>01</b> |
|------------|---------------------------------|------------------------------|---------------------|---------|----------|--------|----------|-----------|--------------|-----------|
| •          | Press the HITS soft key 🕂       | MIC DIR                      | IST. >>>>           |         |          |        | -        | IN 11:00  | JAMES S      |           |
| •          | Press IC (Incoming) soft Key    | - <del>06</del>              | $\rightarrow$       | IC      |          |        |          |           |              | 201       |
| •          | Press <b>↑Prev</b> ↓Next to scr | oll through                  | the last 5          | 0 incom | ing numl | oers — | ****     | CB        | <b>↑Prev</b> | ↓Next     |
|            | Drocs CP coft kov to call ba    | -<br>                        | or on the           | dicplay |          | CB     | 1Prev    | ↓Next     |              |           |

Press **CB** soft key to call back the number on the display

**Note**: If you have a missed call, you will see a on the top left corner. When reviewing your Caller ID, it will show [Missed] when it is the call you've missed.

# <u>Call Forward</u>

- Press Call Fwd Key
- Enter another Extension; or 9 plus phone Number (will take a few seconds to turn on)

To Cancel: Press Call Fwd key, press the 🛞 key, then press Speaker 📟 key

# **Button Programming**

- Press Feature Feeders key
- · Press key to be programmed
- Enter Extension number OR 9 + Phone number (if long distance it requires a 1 in front of the number)
- Press Feature Feedback

Note: When you program a one touch key it uses one of your station speed dial number (see below)

#### Station Speed Dial Programming:

- Press **DIR** Soft key **MIC DIR HIST.** >>>>
- · Scroll ↑↓ to choose an available bin 00-19
- · Press Entry, then Number
- Enter 9 plus the desired number, then press Set
- · Press Name: spell out name (press # after each letter)
- · Press Set
- · Press Ok

<u>To Use</u>: Lift Handset, Press Redial key, then enter the speed dial number you'd like to call OR Press DIR Soft key, Scroll  $\uparrow \downarrow$  to scroll through the speed dials or key in name, then press search. Lift handset to call.

# <u>Ring Tone</u>:

- Press Feature Emergy Key, then press 3
- Press 3 repeatedly to scroll through the ringtones.
- Press Feature Fee Key to Save

# <u>Ring Volume</u>:

- Press Feature 🔤 Key, then press 3
- Use arrows to adjust the volume up and down
- · Press Feature 🔤 Key to Save



